

## **PHC10-3 PLUS switch settings**

The table below summarises the differences between the switch settings that allow correct configuration of the PHC10-3 PLUS when replacing a PHC10-2:

PHC10-2 switch	PHC10-3 PLUS switch equivalent	Function	UP	DOWN
1	1#	Baud rate		
2	2#	Baud rate		
3	3#	Baud rate		
4				
5				
6	4*#	Stop bit	2 stop bits	1 stop bit
7	5*#	CTS protocol	CTS on	CTS off
8	6*#	LF protocol	LF on	LF off
9	9#	Command set	Extended	Basic
10	10	Probe reset time	2 (extended)	1 (standard)
11	7	PPOFF	PPOFF - active during head index	PPOFF - inactive during head index
12	8	HCU2 probe, DAMP and probe reset buttons	Enabled	Disabled
13				
14				
15 + 16	12	Output configuration	PICS	DIN
17 + 18	11	Interface connection	PICS or 7 pin DIN operation	5 pin DIN operation only
	13	Probe wire isolation	Machine cable	Multiwire

\* Operational only when basic command set selected (switch 9 down)

# Not required for USB operation default position = down

**NOTE:** Switches 4, 5, 13 and 14 had no function in RS232 PHC10-2. Press the reset switch after making switch position changes to allow the new settings to take effect.

www.renishaw.com/PHC10-3





## **Baud rate selection**

BAUD RATE	SWITCH 1	SWITCH 2	SWITCH 3
300	DOWN	DOWN	DOWN
600	UP	DOWN	DOWN
1200	DOWN	UP	DOWN
2400	UP	UP	DOWN
4800	DOWN	DOWN	UP
9600	UP	DOWN	UP
19200	DOWN	UP	UP

The baud rate is set using switches 1 to 3 as shown below:

**NOTE:** Press the reset switch after making switch position changes to allow the new setting to take effect.

## www.renishaw.com/PHC10-3



📞 +44 (0) 1453 524524

## 🔰 uk@renishaw.com

@ 2011–2024 Renishaw plc. All rights reserved. This document may not be copied or reproduced in whole or in part, or transferred to any other media or language by any means, without the prior written permission of Renishaw.

RENISHAW® and the probe symbol are registered trade marks of Renishaw plc. Renishaw product names, designations and the mark 'apply innovation' are trade marks of Renishaw plc or its subsidiaries. Other brand, product or company names are trade marks of their respective owners. WHILE CONSIDERABLE EFFORT WAS MADE TO VERIFY THE ACCURACY OF THIS DOCUMENT AT PUBLICATION, ALL WARRANTIES, CONDITIONS, REPRESENTATIONS AND LIABILITY, HOWSOEVER ARISING, ARE EXCLUDED TO THE EXTENT PERMITTED BY LAW. RENISHAW RESERVES THE RIGHT TO MAKE CHANGES TO THIS DOCUMENT AND TO THE EQUIPMENT, AND/OR SOFTWARE AND THE SPECIFICATION DESCRIBED HEREIN WITHOUT OBLIGATION TO PROVIDE NOTICE OF SUCH CHANGES.

Renishaw plc. Registered in England and Wales. Company no: 1106260. Registered office: New Mills, Wotton-under-Edge, Glos, GL12 8JR, UK.

Part no.: H-1000-5244-03-A Issued: 04.2024